CDM-600 & CDM-600L Open Network 
Satellite Modems



#### **Overview Typical Users** The CDM-600 and CDM-600L are open network satellite modems, which are fully compliant with IESS-308, Satellite Service -309, -310, -314, and -315 from 64 kbps through T2 and E2. They are available in the following three data Providers rate ranges: Telecom Service Low-Rate variable: 2.4 kbps to 5.0 Mbps Providers Mid-Rate variable: 2.4 kbps to 10.0 Mbps 2.4 kbps to 20.0 Mbps High-Rate variable: Broadcasters In addition, both modems operate in closed network from 2.4 kbps to 20 Mbps. The modems include T1, Offshore E1, T2, and E2 G.703 interfaces, in addition to EIA-422, V.35, EIA-232, and serial LVDS. HSSI is provided by adding the CIC-20 interface converter. The architecture is firmware and FPGA-based, and the internal Enterprise Flash memory allows easy updating via the serial port. The modems offer exceptional flexibility and performance in 1RU enclosures. **Common Applications Features** Intelsat Business Services Mobile Backhaul • CDM-600: 50 to 90 or 100 to 180 MHz IF range D&I++ CDM-600L: 950 to 2000 MHz IF range ESC++ G.703 Trunking Automatic Uplink Power Control (AUPC) Fast acquisition demodulator (± 32 kHz Embedded Distant-end Monitor and Control acquisition range, 64 kbps, Rate 1/2 QPSK: 1 sec (EDMAC) average) Asymmetric loop timing BPSK, QPSK, OQPSK, 8PSK, 16-QAM modulation types • CDM-600: 50 or 75 $\Omega$ , front panel selectable Patented 8-QAM for LDPC CDM-600L: transmit 50 $\Omega$ , receive 50 or 75 $\Omega$ , female Type N connector Data rate range from 2.4 kbps to 20 Mbps Open network compatible and backwards compatible with the CDM-Forward Error Correction choices include Turbo 500/CDM-550, and CDM-550T Product Coding (IESS-315 compliant), Viterbi, Interoperable with SDM-300A. SDM-300L3 (CDM-600L only) Sequential, Reed-Solomon, LDPC and TCM 1:1 and 1:10 redundancy switch available • Intermediate Data Rate (IDR)

#### **Feature Enhancements**

Enhancing the modem's performance is easy. Additional features are added quickly on site, using FAST access codes purchased from Comtech EF Data. To enable these features, simply enter the code at the front panel.

#### **Turbo Product Coding**

The modems offer all traditional FEC methods and incorporate an optional Turbo Product Codec (TPC). TPC is a FEC technique that delivers significant performance improvement when compared to Viterbi with concatenated Reed-Solomon. TPC simultaneously offers increased coding gain, lower decoding delay and significant bandwidth savings.

Two TPC codecs are offered as hardware options:

- The Low-Rate TPC codec operates up to 5 Mbps with limited code rates.
- The High-Rate TPC codec operates up to 20 Mbps, and offers a full range of code rates (5/16 through 7/8, and 0.95) with all
  modulation types from BPSK to 16-QAM



#### **EDMAC Operation**

Special features of the modems are their ability to monitor and control the distant end of a satellite link using a Comtech EF Data proprietary overhead channel. This framed mode is called EDMAC. User data is framed and extra bits are added to pass control, status, and Automatic Uplink Power Control information. This process is completely transparent to the user. An RF transceiver (C-Band and Ku-Band) or Block Up Converter at the distant end of a satellite link may be controlled and monitored from the front panel of the modem using a low data rate FSK signal on the RX IF cable via the EDMAC channel.

#### **Remote Control**

The operator may configure and monitor the modem from the front panel, or through the remote M&C port. Ten complete configurations may be stored in the modem. An event log stores alarm and status information in non-volatile RAM, while the Link Statistics log stores link performance ( $E_b/N_o$  and AUPC performance) for QoS reporting purposes. SatMac, a Windows-based monitor and control program, is available for configuring the local and distant end modems, transceivers, and redundancy switches.

#### Low Density Parity Check (LDPC) Coding and 8-QAM Modulation

A third codec is available as a hardware option. The TPC/LDPC Codec combines all TPC functions of the High-Rate TPC option, plus the following new features:

- Improved performance of LDPC codes at 1/2, 2/3, and 3/4 rates to further improve coding gain and bandwidth efficiency.
- 8-QAM modulation that offers the same bandwidth efficiency of 8PSK but with improved BER performance and tracking in noisy environments. The patented (U.S. patent 7,254,188) 8-QAM modulation was developed by Comtech EF Data in order to take full advantage of the increased coding gain provided by LDPC, while allowing for acquisition and tracking at much lower Eb/No compared to 8PSK.

#### Drop and Insert (D&I++)

Full drop and insert functionality is available as an option. The modems offer two variants of drop and insert (D&I). The first is an Intelsat open network-compliant mode, using the IBS framing (6.7%). The second is CEFD's proprietary enhanced mode, called D&I++. This "n" x 64 kbps mode offers any value of "n" up to 24, and permits the simultaneous use of EDMAC, AUPC (see below) and an ESC circuit at 1/576th of the user data rate. This is achieved with the addition of only 2.2% overhead.

#### ESC++

A high rate overhead channel is now standard in the new enhanced version of the modems. This provides a separate RS-232 channel allowing up to 4.8 kbaud at 64 kbps and up to 38.4 kbaud at 512 kbps. AUPC also operates in this mode.

## **Specifications**

opecifications			
Frequency Range		CDM-600: 50 to 90 or 100 to 180 MHz,	
		CDM-600L: 950 to 2000 MHz,	
		100 Hz frequency resolu	
Input/Output Impedance		CDM-600: 50 or 75 $\Omega$ (f	ront panel
		selectable)	
		CDM-600L: transmit 50 $\Omega$ , receive	
		50 or 75 $\Omega$ , female Type N connector	
Data Interfaces		EIA-422/-530, V.35, Sync EIA-232,	
		G.703 balanced or unbalanced, Low	
		Voltage Differential Sign	
		(using CIC-20 HSSI/LVDS interface	
Data Rate Range		converter)	
(1 bps programmable, and	d fully	independent TX and RX	rates)
Rate		Range	
1/2 BPSK		2.4 kbps to 5.0 Mbps	
1/2 QPSK/OQPSK		4.8 kbps to 10.0 Mbps	
3/4 QPSK/OQPSK		7.2 kbps to 15.0 Mbps	
7/8 QPSK/OQPSK		8.4 kbps to 17.5 Mbps	
2/3 8PSK		4.8 kbps to 20.0 Mbps	
Uncoded		4.8 kbps to 20.0 Mbps	
<b>Turbo Product Coding F</b>	Rates		
Rate	Ra	inge	High-Rate
21/44 BPSK	4.8	3 kbps to 3.2 Mbps	4.77 Mbps
5/16 BPSK	4.8	3 kbps to 2.048 Mbps	3.12 Mbps
1/2 QPSK/OQPSK	4.8	3 kbps to 9.54 Mbps	Turbo Card
3/4 QPSK/OQPSK	_	2 kbps to 5.0 Mbps	15 Mbps
3/4 8PSK8PSK	_	.8 kbps to 5.0 Mbps	20 Mbps
3/4 16-QAM		.4 kbps to 5.0 Mbps	20 Mbps
7/8 QPSK/OQPSK		kbps to 17.5 Mbps	Turbo Card
7/8 8PSK		.6 kbps to 20.0 Mbps	Turbo Card
7/8 16-QAM		.8 kbps to 20.0 Mbps	Turbo Card
0.95 QPSK/OQPSK		1 kbps to 18.888 Mbps	Turbo Card
0.95 8PSK		.6 kbps to 20 Mbps	Turbo Card
Low Density Parity Che		•	
1/2 BPSK		3 kbps to 5.0 Mbps	
1/2 QPSK/OQPSK		4.8 kbps to 10.0 Mbps	
2/3 QPSK/OQPSK		6.4 kbps to 13.3 Mbps	
2/3 8PSK, 8-QAM	9.6	6 kbps to 19.0 Mbps	

3/4 QPSK/OQPSK	7.2 kbps to 15.0 Mbps	
3/4 8PSK, 8-QAM	10.8 kbps to 20.0 Mbps	
3/4 16-QAM	14.4 kbps to 20.0 Mbps	
Scrambling	Mode dependent - ITU V.35 (Intelsat IESS- 308), or externally synchronized (Intelsat IESS-309/-310/-314 or proprietary	
FEC Options		
Viterbi	Rate 1/2 BPSK, QPSK/OQPSK Rate 3/4 and 7/8 QPSK/OQPSK and 16-QAM w/RS	
Pragmatic TCM	8PSK 2/3	
Low-Rate TPC	21/44, 5/16 BPSK, and 3/4 8PSK, 3/4 16-QAM	
High-Rate TPC	21/44, 5/16 BPSK, 1/2, 3/4, 7/8, 0.95 QPSK/OQPSK, 3/4, 7/8, 0.95 8PSK, and 3/4, 7/8 16-QAM	
LDPC	1/2 BPSK, 2/3, 3/4 QPSK/OQPSK, 2/3, 3/4 8PSK, 2/3, 3/4 8-QAM, and 3/4 16-QAM	
Reed-Solomon	Intelsat compliant and proprietary modes available	
Uncoded	BPSK, QPSK/OQPSK	
M&C Interface	EIA-232, EIA-485 (2- or 4-wire)	
Form C Relays	TX, RX traffic alarms and unit faults Backward alarms for IDR and IBS	
Data Interfaces		
Electrical Interface	G.703 (T1, E1, T2, E2), RS-422, V.35, LVDS or Synchronous RS-232 (refer to manual for further information)	
Frame Formats	D4 or ESF for T1, CCS for E1	
Supported	(Also CAS E1 for open network)	
Available nx64 kbps Data Rates	1 to 6, 8, 10, 12, 15, 16, 20, 24 or 30 for open network, 1 to 24 for D&I++ enhanced proprietar	
Electrical Interface	G.703 (T1, E1, T2, E2), RS-422, V.35, LVDS or Synchronous RS-232 (refer to manual for further information)	

# ESC Specifications

IDR (Total Overhead 9	
Voice Orderwire	2 ADPCM (input: 4-wire VF), or 64 kbps data 8 kbps (EIA-422 interface)
Data Orderwire Backward Alarms	Form C contacts, hardware or software mapped
IBS (Total Overhead 1)	(15 x data rate)
ASYNC Data	
Orderwire	1/2000 x data rate
Backward Alarm ESC++	Form C contacts ASYNC RS-232 at 1.2 to 38.4 kbaud
(Refer to manual)	ASYNC RS-232 at 1.2 to 38.4 kbaud
	1
Modulator	
Output	Meets IESS-308/309 power spectral mask
Spectrum/Filtering	
Frequency Stability	CDM600:
	$\pm$ 1.5 ppm, 0° to 50°C (32° to 122°F) (Standard)
	$\pm$ 0.02 ppm, 0° to 50°C (32° to 122°F) (optional)
	CDM600L:
	± 1.0 ppm, 0° to 50°C (32° to 122°F) (Standard)
Llamaaniaa and	± 0.02 ppm, 0° to 50°C (32° to 122°F) (optional)
Harmonics and Spurious	< -55 dBc/4 kHz (Typically < –60 dBc/4 kHz)
Transmit On/Off	55 dB minimum
Ratio	
Phase Noise	< 0.75 degrees RMS double-sided,
	100 Hz to 1 MHz
Output Power	CDM-600: 0 to -20 dBm, 0.1 dB steps,
•	CDM-600L: 0 to -40 dBm, 0.1 dB steps
Accuracy	CDM-600: $\pm$ 0.5 dB over frequency and
	temperature
	CDM-600L: ± 1.5 dB over frequency and
External TX Carrier	temperature By TTL LOW signal
Off	By TTE LOW Signal
TX Terrestrial	Internal (SCT), EXT TT, Loop
Clock Options	Timing from satellite and EXT CLOCK
BUC FSK	CDM-600L Only: Via TX center conductor with
Communications	FSK BUCs
ODU/BUC Voltage	CDM-600L Only: 24 VDC, 4 amps, 100 W
(Optional) BUC 10 MHz	48 VDC, 3.75 amps, 180 W CDM-600L Only: On/Off
	CDM-600L ONLY. ON/ON
Demodulator	
Input Power Range	CDM600: -30 to -60 dBm
input i onor rungo	CDM600L: -130 dBm + 10Log (symbol rate)
	minimum
AGC (CDM-600L	50 dB above minimum
Only)	
Max Composite Level	+35 dBc, up to –5 dBm
Acquisition Range	1 1 1 to 1 22 kl la programmable in 1 kl la stope
	$\pm$ 1 to $\pm$ 32 kHz, programmable in 1 kHz steps
Acquisition Time	Dependent on data rate, FEC and acquisition
	Dependent on data rate, FEC and acquisition range
Acquisition Time	Dependent on data rate, FEC and acquisition range Example: 1 sec average at 64 kbps Rate 1/2
	Dependent on data rate, FEC and acquisition range Example: 1 sec average at 64 kbps Rate 1/2 CDM-600L only:
Acquisition Time	Dependent on data rate, FEC and acquisition range Example: 1 sec average at 64 kbps Rate 1/2
Acquisition Time	Dependent on data rate, FEC and acquisition range Example: 1 sec average at 64 kbps Rate 1/2 CDM-600L only: 12, 18 or 24 VDC, up to 500mA CDM-600L Only: On/Off Met with two adjacent carriers 7 dB higher
Acquisition Time LNB Voltage LNB 10 MHz	Dependent on data rate, FEC and acquisition range Example: 1 sec average at 64 kbps Rate 1/2 CDM-600L only: 12, 18 or 24 VDC, up to 500mA CDM-600L Only: On/Off Met with two adjacent carriers 7 dB higher Guaranteed $E_b/N_0$ , in dB (Typical values in
Acquisition Time LNB Voltage LNB 10 MHz Example BER Performance	Dependent on data rate, FEC and acquisition range Example: 1 sec average at 64 kbps Rate 1/2 CDM-600L only: 12, 18 or 24 VDC, up to 500mA CDM-600L Only: On/Off Met with two adjacent carriers 7 dB higher Guaranteed $E_b/N_0$ , in dB (Typical values in parentheses)
Acquisition Time LNB Voltage LNB 10 MHz Example BER	Dependent on data rate, FEC and acquisition range Example: 1 sec average at 64 kbps Rate 1/2 CDM-600L only: 12, 18 or 24 VDC, up to 500mA CDM-600L Only: On/Off Met with two adjacent carriers 7 dB higher Guaranteed $E_b/N_0$ , in dB (Typical values in parentheses) SK)
Acquisition Time LNB Voltage LNB 10 MHz Example BER Performance Viterbi (B, Q, and OQP	Dependent on data rate, FEC and acquisition rangeExample: 1 sec average at 64 kbps Rate 1/2CDM-600L only: 12, 18 or 24 VDC, up to 500mACDM-600L Only: On/OffMet with two adjacent carriers 7 dB higher Guaranteed $E_b/N_0$ , in dB (Typical values in parentheses)SK) $1/2$ $3/4$ $7/8$
Acquisition Time LNB Voltage LNB 10 MHz Example BER Performance Viterbi (B, Q, and OQP 10 <sup>-5</sup>	Dependent on data rate, FEC and acquisition range Example: 1 sec average at 64 kbps Rate 1/2 CDM-600L only: 12, 18 or 24 VDC, up to 500mA CDM-600L Only: On/Off Met with two adjacent carriers 7 dB higher Guaranteed $E_b/N_0$ , in dB (Typical values in parentheses) SK) 1/2 $3/4$ $7/85.4 (4.9) 6.8 (6.3) 7.7 (7.2)$
Acquisition Time LNB Voltage LNB 10 MHz Example BER Performance Viterbi (B, Q, and OQP 10 <sup>-5</sup> 10 <sup>-7</sup>	Dependent on data rate, FEC and acquisition rangeExample: 1 sec average at 64 kbps Rate 1/2CDM-600L only:12, 18 or 24 VDC, up to 500mACDM-600L Only: On/OffMet with two adjacent carriers 7 dB higher Guaranteed $E_b/N_0$ , in dB (Typical values in parentheses)SK) $1/2$ $3/4$ $7/8$ $5.4$ (4.9) $6.8$ ( $6.3$ ) $7.7$ ( $7.2$ ) $6.7$ ( $6.2$ ) $8.2$ ( $7.7$ ) $9.0$ ( $8.6$ )
Acquisition Time LNB Voltage LNB 10 MHz Example BER Performance Viterbi (B, Q, and OQP 10 <sup>-5</sup> 10 <sup>-7</sup> Sequential	Dependent on data rate, FEC and acquisition rangeExample: 1 sec average at 64 kbps Rate 1/2CDM-600L only:12, 18 or 24 VDC, up to 500mACDM-600L Only: On/OffMet with two adjacent carriers 7 dB higher Guaranteed $E_b/N_0$ , in dB (Typical values in parentheses)SK)1/23/47/85.4 (4.9)6.8 (6.3)7.7 (7.2)6.7 (6.2)8.2 (7.7)9.0 (8.6) (Consult manual for details)
Acquisition Time LNB Voltage LNB 10 MHz Example BER Performance Viterbi (B, Q, and OQP 10 <sup>-5</sup> 10 <sup>-7</sup> Sequential Viterbi Concatenated F	Dependent on data rate, FEC and acquisition rangeExample: 1 sec average at 64 kbps Rate 1/2CDM-600L only:12, 18 or 24 VDC, up to 500mACDM-600L Only: On/OffMet with two adjacent carriers 7 dB higher Guaranteed $E_b/N_0$ , in dB (Typical values in parentheses)SK) $1/2$ $3/4$ $7/8$ $5.4$ (4.9) $6.8$ ( $6.3$ ) $7.7$ ( $7.2$ ) $6.7$ ( $6.2$ ) $8.2$ ( $7.7$ ) $9.0$ ( $8.6$ )
Acquisition Time LNB Voltage LNB 10 MHz Example BER Performance Viterbi (B, Q, and OQP 10 <sup>-5</sup> 10 <sup>-7</sup> Sequential Viterbi Concatenated F (B, Q, and OQPSK)	Dependent on data rate, FEC and acquisition rangeExample: 1 sec average at 64 kbps Rate 1/2CDM-600L only:12, 18 or 24 VDC, up to 500mACDM-600L Only: On/OffMet with two adjacent carriers 7 dB higher Guaranteed $E_b/N_0$ , in dB (Typical values in parentheses)SK)1/23/47/85.4 (4.9)6.8 (6.3)7.7 (7.2)6.7 (6.2)8.2 (7.7)9.0 (8.6) (Consult manual for details)
Acquisition Time LNB Voltage LNB 10 MHz Example BER Performance Viterbi (B, Q, and OQP 10 <sup>-5</sup> 10 <sup>-7</sup> Sequential Viterbi Concatenated F (B, Q, and OQPSK) 10 <sup>-5</sup>	Dependent on data rate, FEC and acquisition range Example: 1 sec average at 64 kbps Rate 1/2 CDM-600L only: 12, 18 or 24 VDC, up to 500mA CDM-600L Only: On/Off Met with two adjacent carriers 7 dB higher Guaranteed $E_b/N_0$ , in dB (Typical values in parentheses) SK) 1/2 $3/4$ $7/85.4$ (4.9) $6.8$ ( $6.3$ ) 7.7 (7.2) 6.7 ( $6.2$ ) $8.2$ ( $7.7$ ) $9.0$ ( $8.6$ ) ( <i>Consult manual for details</i> ) Reed-Solomon 220/200 or 200/180
Acquisition Time LNB Voltage LNB 10 MHz Example BER Performance Viterbi (B, Q, and OQP 10 <sup>-5</sup> 10 <sup>-7</sup> Sequential Viterbi Concatenated F (B, Q, and OQPSK) 10 <sup>-5</sup> 10 <sup>-7</sup>	Dependent on data rate, FEC and acquisition rangeExample: 1 sec average at 64 kbps Rate 1/2CDM-600L only:12, 18 or 24 VDC, up to 500mACDM-600L Only: On/OffMet with two adjacent carriers 7 dB higher Guaranteed $E_b/N_0$ , in dB (Typical values in parentheses)SK)1/23/47/85.4 (4.9)6.8 (6.3)7.7 (7.2)6.7 (6.2)8.2 (7.7)9.0 (8.6) (Consult manual for details)Reed-Solomon 220/200 or 200/1801/23/47/8
Acquisition Time LNB Voltage LNB 10 MHz Example BER Performance Viterbi (B, Q, and OQP 10 <sup>-5</sup> 10 <sup>-7</sup> Sequential Viterbi Concatenated F (B, Q, and OQPSK) 10 <sup>-5</sup>	Dependent on data rate, FEC and acquisition range Example: 1 sec average at 64 kbps Rate 1/2 CDM-600L only: 12, 18 or 24 VDC, up to 500mA CDM-600L Only: On/Off Met with two adjacent carriers 7 dB higher Guaranteed $E_b/N_0$ , in dB (Typical values in parentheses) SK) 1/2 $3/4$ $7/85.4$ (4.9) $6.8$ ( $6.3$ ) 7.7 (7.2) 6.7 ( $6.2$ ) $8.2$ (7.7) $9.0$ ( $8.6$ ) ( <i>Consult manual for details</i> ) Reed-Solomon 220/200 or 200/180 1/2 $3/4$ $7/84.3$ ( $4.0$ ) $5.6$ ( $4.7$ ) $6.5$ ( $6.0$ )

		/		
	<u>1/2</u>	3/4	7/8	0.95
10 <sup>-6</sup>	2.9 (2.6)	3.8 (3.4)	4.3 (4.0)	6.4 (6.0)
10 <sup>-8</sup>	3.3 (2.8)	4.4 (4.0)	4.5 (4.2)	6.9 (6.5)

(Please consult the manual for a performance listing of all FEC types, Code Rates, and Modulation types.)

Receive Buffer	64 to 262144 bits, in 16 bit increments
Receive Clock Options	RX satellite, TX terrestrial, external reference, insert
Clock Tracking	± 100 ppm minimum
External Clock Input	BNC connector, 2.4 kHz to 20 MHz
External Reference Input (Optional)	SMA female, 1, 2, 5, 10 or 20 MHz
Monitor Functions	$E_b/N_0$ , frequency offset, BER, buffer fill status, RX receive signal level

#### **Drop And Insert**

Electrical Interface		G.703, RS-422 or V.35 (T1 or E1)
Frame Formats Supported		D4 or ESF for T1, CCS for E1
		(Also CAS E1 for open network)
Available n x 64 kbps Data Rates		1 to 6, 8, 10, 12, 15, 16, 20, 24 or
		30 for Open Network
		1 to 24 for D&I++ enhanced
		proprietary
Accessories		
		1:1 Modem Redundancy Switch
	(With CRS	S-170A L-Band IF Switch – CDM-

#### 600L) CRS-300 CRS-300 1:N Modem Redundancy Switch

## Available Options

How Enabled	Option	
N/A	Variable data rate to 5 Mbps (standard)	
FAST	Variable data rate to 10 Mbps	
FAST	Variable data rate to 20 Mbps	
FAST	8PSK modulation (and 8-QAM if TPC/LDPC	
	Codec is installed – CDM-600)	
FAST	CDM-600: LDPC to 10 Mbps	
FAST	CDM-600: LDPC to 20 Mbps	
FAST	16-QAM modulation	
FAST	IBS operation	
FAST	IBS with high-rate IBS ESC operation	
FAST	IDR operation	
FAST	Drop & insert operation	
	(open network and D&I++)	
FAST	2 Audio IBS Operation	
Hardware	Turbo Codec – low-rate 5 Mbps (21/44, 5/16, 3/4)	
Hardware	Turbo Codec – high-rate 20 Mbps (21/44, 5/16, 1/2, 3/4, 7/8, 0.95)	
Hardware	CDM-600: High-stability internal reference (2 x 10 <sup>-8</sup> ) with external input capability CDM-600L: internal reference 1.0 ppm (standard, not with BUCs) or 0.02 ppm (optional)	
Hardware	CIC-20 HSSI interface converter	
Hardware	TPC/LDPC Codec (Base to 5 Mbps - CDM- 600)	
Hardware	RX Type F or Type N connector (CDM-600L)	
Hardware	CDM-600L: ODU PS 24 VDC, 100 W, AC or DC input	
Hardware	CDM-600L: ODU PS 48 VDC, 180 W, AC or DC input	

#### Environmental & Physical

	lysical
Temperature	Operating: 0 to 50°C (32 to 122°F) Storage: -25 to 85°C (-13 to 185°F)
Power Supply	100 to 240 VAC, 50/60 Hz 38 to 60 VDC (optional DC)
Power Consumption (see manual)	55 W max. AC, w/o BUC power supply 290 W max. AC, with BUC power supply
<b>Dimensions (1RU)</b> (height x width x depth)	
CDM-600	1.72" x 19" x 13.1" (4.4 x 48.2 x 33.3 cm)
CDM-600L	1.72" x 19" x 18.0" (4.4 x 48.2 x 45.7 cm)
Weight	
CDM-600	10 lbs (4.5 kg) max.
CDM-600L	10 lbs (4.5 kg) max., w/o BUC power supply 11.6 lbs (5.3 kg) max., with BUC power supply





CDM-600 Open Network Satellite Modem back panel



CDM-600L Open Network Satellite Modem back panel



2114 West 7th Street, Tempe, Arizona 85281 USA Voice: +1.480.333.2200 • Fax: +1.480.333.2540 • Email: sales@comtechefdata.com

See all of Comtech EF Data's Patents and Patents Pending at http://patents.comtechefdata.com
Comtech EF Data reserves the right to change specifications of products described in this document at any time without notice and without obligation to notify any person of such changes. Information in this
document may differ from that published in other Comtech EF Data documents. Refer to the website or contact Customer Service for the latest released product information.
© 2012 Comtech EF Data